
ConnectBox V6 - Quick Start Guide



The ConnectBox is a self contained WiFi hotspot allowing the user to distribute pre-loaded media content simultaneously to up to 17 users. It is battery powered with a run time between charges typically 6 to 8 hours. The following are simplified instructions for its use. More detailed information can be found in the **full document** at:

https://github.com/ConnectBox/website_posts/blob/master/ConnectBox-GettingStarted_V6.pdf

Interfacing with the ConnectBox:

- 1. On/Off switch
- 2. USB port
- 3. Charging port (micro USB)
- 4. OLED Display
- **5.** LEDs: Green=ON, Amber=Ready, Red=Charging
- **6.** Navigation Buttons
- 7. uSD access port
- 8. Security Mount

Adding Content:

- Format a USB stick for FAT32
- Store content on the stick beginning at the root level. (Folders and sub-folders are allowed and icons are supported)
- Plug the USB stick into the USB port on the ConnectBox
- Many more details at in the full document

Initial setup:

- Fully charge the unit with power off. Initial charging will take 4 - 24 hours depending on existing charge
- Add content to the unit (see Adding Content)
- Power the unit ON
- Connect to unit using phone (SSID: "ConnectBox - Free Media")
- Follow prompts on phone to connect. If necessary, close browser and open a new browser at http://wi.fi
- Navigate folders to view content

Screen Display:

- Turn screen on by pushing either Navigation Button
- Use buttons to navigate forward ("^") and backward ("v") through the screens
- Screens display:
 - General Info
 - Connection Info
 - Battery info
 - Statistics (daily, montly, weekly)
 - Administrator function access (default password: connectbox)
- Many more details at in the **full document**